



## Impact Series 250-Watt Audio Amplifier MODEL: IMPACT ADCS 21

Model	IMPACT ADCS 21
Amplifier	Class D
THD	THD+N (@ 1 kHz): < 0.1%
Crosstalk (@ 1 kHz)	> 70 dB
Impedance balanced	12 k $\Omega$
Frequency Response	( $\pm$ 3 dB) 20 Hz - 20 kHz
Signal / Noise	> 90 dB
Power Supply	100 ~ 240 V AC / 50 ~ 60 Hz
Power Consumption	224 W, Standby 0.8 Watt (30 min standby time)
Protection:	DC Short circuit, Overheating, Over load, Signal limiting
Cooling	Coling fan
Inputs Sensitivity	(1W/1m) 0 dB (1V RMS)
Connector	XLR female with Male Linkthrough / Block balanced Inputs
Output port	Speak on compatible & 2-pin Euro Terminal Block (5.08 mm)
RMS Power	8 $\Omega$ Stereo- 2 x 130 W, 4 $\Omega$ Stereo- 2 x 250 W , 8 $\Omega$ Bridge- 500 W

\*Due to continuous product development, the specifications may change without prior notice.

\*\*Product image(s) are for illustrative purposes only and may differ from the actual product.



Corporate Office:

A-66, Sector-4, Noida, District Gautam Buddha Nagar, U.P., India - 201301

☎ 0120-4051700/800 ☎ 0120-4051827 ✉ info@globusinfocom.com

☎ For Sales: 0 85888 39434 🌐 www.globusinfocom.com