



## Impact Series 250-Watt Audio Amplifier MODEL: IMPACT ADCS 41

Model	IMPACT ADCS 41
Amplifier	Class D
THD	THD+N (@ 1 kHz): < 0.1%
Cooling	Colling Fan
Power Consumption	500 W, Standby 5 Watt
Crosstalk (@ 1 kHz)	> 70 dB
Power Supply	Switching mode, 100~240V AC / 50~60Hz
Frequency Response	( $\pm 3$ dB) 20 Hz - 20 kHz
Signal / Noise	> 90 dB
Connector	XLR female with Male Linkthrough / Block balanced Inputs
Protection	Overheating, Overload, Signal limiting, DC Short circuit
Inputs Sensitivity	0 dB (1V RMS)
Impedance balanced	12 k $\Omega$
Output port	2-pin Euro Terminal Block (Pitch - 5.08 mm)
RMS Power	4 $\Omega$ Stereo: 4 x 250W, 8 $\Omega$ Stereo: 4 x 130W, 8 $\Omega$ Bridge: 2 x 500 W

\*Due to continuous product development, the specifications may change without prior notice.

\*\*Product image(s) are for illustrative purposes only and may differ from the actual product.



Corporate Office:

A-66, Sector-4, Noida, District Gautam Buddha Nagar, U.P., India - 201301

☎ 0120-4051700/800 ☎ 0120-4051827 ✉ info@globusinfocom.com

☎ For Sales: 0 85888 39434 🌐 www.globusinfocom.com